

JNCA-2

Network Control Annunciator



General

The JNCA-2 is a second-generation Network Control Annunciator for the **NOTI•FIRE•NET™** network, compatible for use with nodes such as the IFC2-3030, IFC-3030, IFC-320, IFC-640 and IFC2-640 fire alarm control panels, as well as first-generation JNCA Network Control Annunciators. Additionally, the JNCA-2 may be configured with JDVC Series products (JDVC, JDVC-EM, JDVC-EMF, and JDVC-EMSF) to create one or more Digital Audio Command Centers on **NOTI•FIRE•NET**. The JNCA-2 provides system control and display capabilities for all, or for selected network nodes.

The JNCA-2 display consists of a 640-character backlit LCD display, and a control interface consisting of “soft” keys used to navigate screen menus, “hard” keys with fixed control functions, and a QWERTY keypad.

When connected to one or more networked panels the JNCA-2 provides network control and status/history display capabilities. It may also be configured as the Primary Display for displayless nodes on the network.

Hardware Features

- Listed to UL Standard 864, 9th edition.
- Full supervision of all inputs and network integrity.
- Enhanced-format 640-character LCD display with backlighting.
- ACS bus for LED or graphic annunciators (EIA-485).
- Optically isolated printer interface (EIA-232).
- 11 LED status indicators: Power, Controls Active, Fire Alarm, Pre-Alarm, Security, Alert, Supervisory, Trouble, Signal, Silence, CPU Failure, Point Disabled, Other Event.
- Alphanumeric QWERTY rubber keypad.
- Four status relays: Alarm, Trouble, Supervisory, Security (Form-C).
- Nonvolatile real-time clock can be synchronized with network by master node.
- Optional Security Keyswitch enable Keypad functions.
- Optional Security Tamper switch.
- Supports up to 32 remote ACS annunciators and modules.
- Requires 24 VDC, and a network connection.
- RDP port for LCD-160 or terminal mode LCD-80.

NOTE: *NCA-2 Firmware version 14.0 (and higher) can support LCD-160 on the RDP port, or LCD-80 in terminal mode, but not both at the same time.*

Function Features

- Individual Enable/Disable or Group Enable/Disable local for networked compatible panels.
- Control ON/OFF networked compatible panel control points.
- Read Status networked compatible panel points and zones.
- Network paging control/HVAC control requires SCS series.
- Network-wide: Acknowledge, Silence, Reset.
- Lamp Test (local to JNCA-2).
- History Buffer (1000 Alarm events; 4000 System events).
- Print JNCA-2 programming and history reports.
- Report status of networked panels and their respective field devices to a central station via a single UDACT.
- One Master level, nine User level passwords. The Master can assign each User access levels (programming, alter status).
- Interactive Summary Event Count display, event handling package.
- Online programming and alter-status programs.
- Intuitive user guidance program including interactive soft keys.
- Enhanced Read Status/Alter Status displays.



JNCA-2 in JABS-2D backbox

- New history filters for report displaying and printing: All Events, Only Alarms, Only Troubles, Only Supervisory, Only Security, Time Interval, Point Range.
- Fully programmable node-mapping subsystem.
- Advanced/Basic Walk-Test program.
- Timer control for Auto Silence, AC Fail Delay.
- Meets Canadian ULC display requirements.
- Environmental adjustment controls to maximize LCD legibility.
- Meets NFPA requirements for Firefighter Smoke Control Station (FSCS) and HVAC.

JNCA-2 Indicators and Controls

LED INDICATORS

- **POWER** (green) illuminates when 24 VDC power is applied; LED goes out if power is removed and JNCA-2 is using a battery.
- **CONTROLS ACTIVE** (green) illuminates to indicate that the JNCA-2 control functions are active.
- **FIRE ALARM** (red) illuminates when at least one fire alarm event exists; flashes when any of these events remain unacknowledged.
- **PRE-ALARM** (red) illuminates when at least one pre-alarm event exists; flashes when any of these events remain unacknowledged.
- **SECURITY** (blue) illuminates when at least one security event exists; flashes when any of these events remain unacknowledged.
- **SUPERVISORY** (yellow) illuminates when at least one supervisory event exists (i.e., sprinkler valve off normal, low pressure, fire pump running, guard's tour, etc.); flashes when any of these events remain unacknowledged.
- **SYSTEM TROUBLE** (yellow) illuminates when at least one trouble event exists; flashes when any of these events remain unacknowledged.
- **OTHER EVENT** (yellow) illuminates for any category of event not listed above; flashes when any of these events remain unacknowledged.

- **SIGNALS SILENCED** (yellow) illuminates if the JNCA-2 Silence key has been pressed or if any other node sent a Network Silence command; flashes if only some points on a node are silenced.
- **POINT DISABLED** (yellow) illuminates when at least one disable exists on the network or in the system.
- **CPU FAILURE** (yellow) activated by the watchdog timer hardware, indicates an abnormal hardware or software condition. Contact technical support.

FIXED FUNCTION KEYS

- **ACKNOWLEDGE**
- **SIGNAL SILENCE**
- **SYSTEM RESET**
- **DRILL**
- **FIRE ALARM SCROLL/DISPLAY**
- **SECURITY SCROLL/DISPLAY**
- **SUPERVISORY SCROLL/DISPLAY**
- **TROUBLE SCROLL/DISPLAY**
- **OTHER EVENT SCROLL/DISPLAY**

The five keys labeled SCROLL/DISPLAY allow the user to scroll through messages for the particular event type. For example, pressing the FIRE ALARM SCROLL/DISPLAY key will scroll through all fire alarm events, as details of each are shown in the display area of the JNCA-2.

NOTE: The OTHER EVENT SCROLL/DISPLAY key also scrolls between Pre-Alarm and Disabled events.

- **ACKNOWLEDGE** – press this key to acknowledge off all active events.
- **SIGNAL SILENCE** – press this key to turn off all control modules, notification appliance circuits, and panel output circuits that have been programmed as Silenceable.
- **SYSTEM RESET** – press this key to clear all latched alarms and other events and turn off event LEDs.
- **DRILL HOLD 2 SEC** – press this key, holding it down for two seconds, to activate all silenceable output circuits.

SPECIAL FUNCTION KEYS

- **PRINT SCREEN** – press this key to print what is currently on the LCD screen.
- **LAMP TEST** – press this key to test the LED indicators on the left of the keypad and to check firmware revision numbers.
- **NEXT SELECTION/PREVIOUS SELECTION** – these keys are used when setting parameters in JNCA-2 data fields; for example, choosing a device type as a filter for requesting a Node History.
- **BATTERY LEVEL** – press this key to display voltage and charging current level for system batteries. Displays levels for local AMPS-24(E) or AMPS-24(E) connected to associated IFC2-3030 or IFC-3030 node.

Specifications

Temperature and humidity ranges: This system meets NFPA requirements for operation at 0°C to 49°C (32°F to 120°F); and at a relative humidity (noncondensing) of 85% at 30°C (86°F) per NFPA, and 93% ± 2% at 32°C ± 2°C (89.6°F ± 1.1°F) per ULC. However, the useful life of the system's standby batteries and the electronic components may be adversely affected by extreme temperature ranges and humidity. Therefore, it is recommended that this system and all peripherals be installed in an environment with a nominal room temperature of 15°C to 27°C (60°F to 80°F). Product weight is 3 lbs (1.36 kilograms).

ELECTRICAL REQUIREMENTS

The JNCA-2 may be powered from a Main Power Supply AMPS-24(E) (see data sheet JCI-6883) mounted in a separate cabinet (see specifications below); or from any UL Listed non-resettable 24 VDC source from a compatible fire panel (see panel data sheets). The battery on the JNCA-2 motherboard is for RTC and SRAM; holds the history memory through power failure. Replacements are available (P/N 31004). Power source: 1) AMPS-24 (120 VAC, 50/60 Hz, 4.5 A maximum) or AMPS-24E (240 VAC, 50/60 Hz, 2.25 A maximum) power supply; 2) the IFC-640, IFC2-640 and IFC-320 on-board power supply; or 3) a supervised +24 VDC power supply that is UL/ULC-listed for fire protective service. The current of the JNCA-2 is 400 mA with backlight and 200 mA with the backlight off.

Agency Listings and Approvals

These listings and approvals apply to the JNCA-2. In some cases, certain modules or applications may not be listed by certain approval agencies, or listing may be in process. Consult factory for latest listing status.

- UL / ULC Listed: file S1570.
- FM approved.
- MEA approved: 232-06-E Vol. 2.

Product Line Information

JNCA-2: Network Control Annunciator. Requires a NCM-W or NCM-F network communications module for networking. In direct connect applications NCM not required.

NCM-W, NCM-F: Standard Network Communications Modules. Wire and multi-mode fiber versions available. See JCI-6861.

HS-NCM-W/MF/SF/WMF/WSF/MFSF: High-speed network communications modules. Wire, single-mode fiber, multi-mode fiber, and media conversion models are available. See JCI-60482.

JABS-2D: Annunciator Backbox, Surface, black. Mounts one JNCA-2 and one NCM-W/F.

JABS-2DR: Same as above, but red.

CHS-2D: Chassis, required whenever the JNCA-2 is mounted in an JABS-2D(R).

CHS-M3: Chassis, mounts a JNCA-2 in a single row of a CAB-4 Series cabinet.

CA-2: Chassis, Audio, 2 rows. Mounts a JNCA-2 and the JDVC Digital Voice Command in two rows of a CAB-4 Series cabinet.

DP-DISP: Annunciator Dress Plate. Dress plate is used when JNCA-2 is mounted in the top row of a CAB-4 Series cabinet with a CHS-M3 chassis.

NCA-2RETRO: Kit for retrofit mounting the JNCA-2 to a DP-DISP dress plate.

NCA/640-2-KIT: Mounting kit for directly mounting the JNCA-2 to JCPU2-640 chassis.

LCD-160: 160 character LCD annunciator

LCD-80: 80 character LCD annunciator

TR-ABS2D: Trim ring for semi-flush mounting of ABS-2D

NOTIFIER® is a registered trademark and **NOTI•FIRE•NET™** is a trademark of Honeywell International Inc.

©2009 by Honeywell International Inc. All rights reserved. Unauthorized use of this document is strictly prohibited.

This document is not intended to be used for installation purposes.
We try to keep our product information up-to-date and accurate.
We cannot cover all specific applications or anticipate all requirements.
All specifications are subject to change without notice.



Made in the U.S.A.

For more information, contact Johnson Controls Field Support Center.
507 East Michigan Street, Milwaukee, WI 53202 www.johnsoncontrols.com